



AN AFFORDABLE ALTERNATIVE TO CONVENTIONAL EMERGENCY LIGHTING, THE UP SERIES IS A FLUORESCENT BALLAST WHICH ENHANCES EXISTING AC FIXTURES BY ILLUMINATING 1 OR 2 LAMPS DURING A POWER FAILURE.

DIMENSIONS

UP160	UP80-2
HEIGHT: 16-3/8"	HEIGHT: 13"
WIDTH: 3"	WIDTH: 2-1/2"
DEPTH: 3"	DEPTH: 1-1/2"

ALL OTHERS
 LENGTH 9-1/2"
 WIDTH 2-3/8"
 HEIGHT 1-1/2"

FACTORY OPTIONS

- TMK** TOP MOUNT KIT
- FC** FLEX CORD (PER FT.)
- RTSK** REMOTE TEST SWITCH KIT



ORDERING INFORMATION

UP40
SERIES

-TMK
OPTIONS

SERIES FEATURES



- ▶ SOLID STATE CHARGER
- ▶ DUAL VOLTAGE TRANSFORMER FOR 120/277 VAC OPERATION
- ▶ MAXIMUM INPUT RATING
 120VAC 60 Hz 4.0 WATT
 277VAC 60 Hz 4.0 WATT



- ▶ FOR USE ON SINGLE OR DOUBLE LAMPS
- ▶ ILLUMINATES RAPID START, INSTANT START, HIGH OUTPUT, SLIMLINE, CIRCLINE, U-SHAPED, OR COMPACT LAMPS



- ▶ SEALED NICKEL CADMIUM BATTERY
- ▶ MAINTENANCE FREE

- ▶ CONVERTS FLUORESCENT FIXTURES TO EMERGENCY LIGHTING
- ▶ PROVIDES 1.5 HOUR ILLUMINATION FOR SINGLE OR DOUBLE LAMPS
- ▶ COMPLETELY SELF-CONTAINED INSIDE OR ABOVE LIGHTING FIXTURE
- ▶ COMPACT STEEL HOUSING
- ▶ CONVENIENT LENGTH LEAD WIRES
- ▶ TEST SWITCH
- ▶ RED (POWER ON) INDICATOR
- ▶ UL LISTED
- ▶ OPERATING RANGE: 50° - 140° F
- ▶ WARRANTY: 2-5 YEARS

MODEL NUMBERS



LAMPS OPERATED

Linear Lamps	QUA.	MODEL NUMBERS						
		500 Lumens	700 Lumens	1300 Lumens	3000 Lumens	650 Lumens	650 Lumens	650 Lumens
2' - 4' Rapid, Instant, Energy Saving, T8 and T12	1	X	X	X	X			
2' - 4' Rapid, Instant, Energy Saving, T8 and T12, HO & VHO	2		⓪	⓪	⓪			
5' - 8' Rapid, Instant, Energy Saving, T8 and T12, HO & VHO	1		X	X	X			
20W - 40W Circline	1	X	X	X	X			
20W - 40W Circline	2		X	X	X			

Compact Lamps

5, 7, 9, & 13 Watt Twin Tube (2 pin)	1					X		
9W - 13W USA Quad Tube (2 pin)	1					X		
18W - 26W Quad Tube (2 pin)*	1						X	
10W - 26W Quad Tube (4 pin)	1 or 2							X
18W - 39W Long compact	1							X
40 Watt Biax	1		X	X	X			
50 Watt Biax	1			X				
55 Watt Biax	1			X				
18W - 26W Triple Tube (4 pin)	1 or 2							X
32W - 42W Triple Tube (4 pin)	1							X

* 22 & 28 WATT 15mm LAMPS ARE NOT COMPATIBLE.
 ⓪ NOTE: TWO LAMP EMERGENCY IS NOT POSSIBLE WITH ALL ELECTRONIC BALLASTS. CONSULT CUSTOMER SERVICE FOR SPECIFIC BALLAST COMPATIBILITY.